

TEKSAN PORTABLE
GENERATOR SERIES

TEKSAN
mini

TM8300EX

Gasoline Generator



CLEAN ENERGY WITH
STAGE V ENGINES



EASY AND
SAFE USAGE



LOW EMISSIONS,
HIGH EFFICIENCY



LUBE LEVEL
INDICATOR



AUTOMATIC
CIRCUIT BREAKER



BOTH DURABLE
AND PRACTICAL

TM8300EX

Gasoline Generator



	SPECIFICATIONS	TEKSAN Mini GASOLINE GENERATOR
	Model	TM8300EX
Output Power	Starting Power	8300W
	Running Power	7500W
Engine	Engine Type	17.0HP, 4-Stroke, Single cylineder, OHV, Air cooled
	Displacement	459cc
	Maximum Power Output	11.5KW/4000rpm
	Starting System	Recoil + Electric Starting
	Fuel	Gasoline
	Fuel Tank Capacity	25L
	Fuel Consumption 25% (l/h)	1,93
	Fuel Consumption 50% (l/h)	2,80
	Fuel Consumption 75% (l/h)	3,36
	Fuel Consumption 100% (l/h)	4,72
Alternator	AC Frequency	50Hz
	Rated AC Voltage	230V
	Power Factor cosΦ	1
	Phase	Single-phase
Configuration	Electric Starting System	✓
	Automatic Voltage Regulator	✓
	Fuel Meter	✓
	Oil Warning System	✓
	Digital Display	✓
	12VDC Output	✓
	AC Circuit Breaker	✓
	2-wheel transport kit	✓
	Automatic Decompression System	✓
	Brush Alternator	✓
Dimensions & Weight	Box Dimensions (L x W x H)	810 × 575 × 575 mm
	Dry Weight	102,5 kg

Teksan reserves the right to change the information contained in this document without notice.



+90 444 8576
www.teksan.com
info@teksan.com