

**TEKSAN
INVERTER PORTABLE
GENERATOR SERIES**

TEKSAN
mini

TM1000I

Gasoline Generator



**CLEAN ENERGY WITH
STAGE V ENGINES**



**EASY AND
SAFE USAGE**



**LOW EMISSIONS,
HIGH EFFICIENCY**



**LUBE LEVEL
INDICATOR**



**AUTOMATIC
CIRCUIT BREAKER**



**BOTH DURABLE
AND PRACTICAL**

TM1000I

Inverter Portable Generator



	SPECIFICATIONS	TEKSAN Mini INVERTER PORTABLE GENERATOR
	Model	TM1000I
Output Power	Starting Power	1000W
	Running Power	900W
Engine	Engine Type	1.9HP, 4-Stroke, Single cylineder, OHV, Air cooled
	Displacement	49,7cc
	Maximum Power Output	1000W
	Starting System	Recoil Starting
	Fuel	Gasoline
	Fuel Tank Capacity	2,8L
	Fuel Consumption 25% (l/h)	0,24
	Fuel Consumption 50% (l/h)	0,36
	Fuel Consumption 75% (l/h)	0,53
	Fuel Consumption 100% (l/h)	0,72
Alternator	AC Frequency	50Hz
	Rated AC Voltage	230V
	Power Factor cosΦ	1
	Phase	Single-phase
Configuration	Electric Starting System	
	Fuel Meter	✓
	Oil Warning System	✓
	Digital Display	
	12VDC Output	✓
	AC Circuit Breaker	✓
	2-wheel transport kit	
	Automatic Decompression System	✓
Dimensions & Weight	Box Dimensions (L x W x H)	510 × 350 × 450 mm
	Dry Weight	17,5 kg

Teksan reserves the right to change the information contained in this document without notice.



+90 444 8576
www.teksan.com
info@teksan.com