

**TEKSAN
INVERTER PORTABLE
GENERATOR SERIES**

TEKSAN
mini

TM3000I *Gasoline Generator*



**CLEAN ENERGY WITH
STAGE V ENGINES**



**EASY AND
SAFE USAGE**



**LOW EMISSIONS,
HIGH EFFICIENCY**



**LUBE LEVEL
INDICATOR**



**AUTOMATIC
CIRCUIT BREAKER**



**BOTH DURABLE
AND PRACTICAL**

TM3000I

Inverter Portable Generator



	SPECIFICATIONS	TEKSAN Mini INVERTER PORTABLE GENERATOR
	Model	TM3000I
Output Power	Starting Power	3200W
	Running Power	3000W
Engine	Engine Type	5.6HP, 4-Stroke, Single cylineder, OHV, Air cooled
	Displacement	171cc
	Maximum Power Output	3200W
	Starting System	Recoil Starting
	Fuel	Gasoline
	Fuel Tank Capacity	6,8L
	Fuel Consumption 25% (l/h)	0,79
	Fuel Consumption 50% (l/h)	1,11
	Fuel Consumption 75% (l/h)	1,48
	Fuel Consumption 100% (l/h)	1,91
Alternator	AC Frequency	50Hz
	Rated AC Voltage	230V
	Power Factor cosΦ	1
	Phase	Single-phase
Configuration	Electric Starting System	
	Fuel Meter	✓
	Oil Warning System	✓
	Digital Display	✓
	12VDC Output	✓
	AC Circuit Breaker	✓
	2-wheel transport kit	✓
	Automatic Decompression System	✓
Dimensions & Weight	Box Dimensions (L x W x H)	675 × 480 × 490 mm
	Dry Weight	40,7 kg

Teksan reserves the right to change the information contained in this document without notice.



+90 444 8576
www.teksan.com
info@teksan.com